

麻省理工学院
电气工程与计算机科学系
6.013 公式表

1、在圆柱坐标系和球坐标系中的微分算子

$r, \phi,$ 和 z 是圆柱坐标, 并且 $\hat{i}_r, \hat{i}_\phi,$ 和 \hat{i}_z 是对应坐标的单位增量,

$$\nabla U = \text{grad} U = \hat{i}_r \frac{\partial U}{\partial r} + \hat{i}_\phi \frac{1}{r} \frac{\partial U}{\partial \phi} + \hat{i}_z \frac{\partial U}{\partial z}$$

$$\nabla \cdot \vec{A} = \text{div} \vec{A} = \frac{1}{r} \frac{\partial (rA_r)}{\partial r} + \frac{1}{r} \frac{\partial A_\phi}{\partial \phi} + \frac{\partial A_z}{\partial z}$$

$$\nabla \times \vec{A} = \text{curl} \vec{A} = \hat{i}_r \left(\frac{1}{r} \frac{\partial A_z}{\partial \phi} - \frac{\partial A_\phi}{\partial z} \right) + \hat{i}_\phi \left(\frac{\partial A_r}{\partial z} - \frac{\partial A_z}{\partial r} \right) + \hat{i}_z \left(\frac{1}{r} \frac{\partial (rA_\phi)}{\partial r} - \frac{1}{r} \frac{\partial A_r}{\partial \phi} \right)$$

$$\nabla^2 U = \text{div grad} U = \frac{1}{r} \frac{\partial}{\partial r} \left(r \frac{\partial U}{\partial r} \right) + \frac{1}{r^2} \frac{\partial^2 U}{\partial \phi^2} + \frac{\partial^2 U}{\partial z^2}$$

$r, \theta,$ 和 ϕ 是球坐标, $\hat{i}_r, \hat{i}_\theta,$ 和 \hat{i}_ϕ 是对应坐标的单位增量,

$$\nabla U = \text{grad} U = \hat{i}_r \frac{\partial U}{\partial r} + \hat{i}_\theta \frac{1}{r} \frac{\partial U}{\partial \theta} + \hat{i}_\phi \frac{1}{r \sin \theta} \frac{\partial U}{\partial \phi}$$

$$\nabla \cdot \vec{A} = \text{div} \vec{A} = \frac{1}{r^2} \frac{\partial (r^2 A_r)}{\partial r} + \frac{1}{r \sin \theta} \frac{\partial (A_\theta \sin \theta)}{\partial \theta} + \frac{1}{r \sin \theta} \frac{\partial A_\phi}{\partial \phi}$$

$$\nabla \times \vec{A} = \text{curl} \vec{A} = \hat{i}_r \left(\frac{1}{r \sin \theta} \frac{\partial (A_\phi \sin \theta)}{\partial \theta} - \frac{1}{r \sin \theta} \frac{\partial A_\theta}{\partial \phi} \right) + \hat{i}_\theta \left(\frac{1}{r \sin \theta} \frac{\partial A_r}{\partial \phi} - \frac{1}{r} \frac{\partial (rA_\phi)}{\partial r} \right) + \hat{i}_\phi \left(\frac{1}{r} \frac{\partial (rA_\theta)}{\partial r} - \frac{1}{r} \frac{\partial A_r}{\partial \theta} \right)$$

$$\nabla^2 U = \text{div grad} U = \frac{1}{r^2} \frac{\partial}{\partial r} \left(r^2 \frac{\partial U}{\partial r} \right) + \frac{1}{r^2 \sin \theta} \frac{\partial}{\partial \theta} \left(\sin \theta \frac{\partial U}{\partial \theta} \right) + \frac{1}{r^2 \sin^2 \theta} \frac{\partial^2 U}{\partial \phi^2}$$

2. 拉普拉斯方程的解

A. 直角坐标系, 两维 (与 z 无关):

$$\Phi = e^{kx} (A_1 \sin ky + A_2 \cos ky) + e^{-kx} (B_1 \sin ky + B_2 \cos ky)$$

(或用 $\sinh kx$ 和 $\cosh kx$ 替代 e^{kx} 和 e^{-kx}) .

$$\Phi = Axy + Bx + Cy + D; (k = 0)$$

B. 圆柱坐标系, 两维 (与 z 无关):

$$\Phi = r^n (A_1 \sin n\phi + A_2 \cos n\phi) + r^{-n} (B_1 \sin n\phi + B_2 \cos n\phi)$$

$$\Phi = \ln \frac{R}{r} (A_1 \phi + A_2) + B_1 \phi + B_2; (n = 0)$$

C. 球坐标系, 两维 (与 ϕ 无关)

$$\Phi = Ar \cos \theta + \frac{B}{r^2} \cos \theta + \frac{C}{r} + D$$